

Figure 1 illustrates the stages of chick development from fertilization to hatching. The diagrams are arranged vertically and labeled with numbers 1 through 12. The stages are: 1. Fertilized egg, 2. Cleavage, 3. Two-cell stage, 4. Four-cell stage, 5. Morula stage, 6. Gastrula stage, 7. Early neurulation, 8. Late neurulation, 9. Early hatching, 10. Late hatching, 11. Hatched chick, and 12. Hatched chick.

Background of the Invention:

This invention relates to a speech coder for coding a speech signal with a high quality at a low bit rate, a speech decoder, a speech coding method, and a speech decoding method.

As a method for coding a speech signal at a high efficiency, CELP (Code Excited Linear Predictive Coding) is known in the art, and is described, for example, in M. Schroeder and B. Atal, "Code-excited linear prediction: High quality speech at very low bit rates" (Proc. ICASSP, pp. 937-940, 1985: hereinafter referred to as Document 1), Kleijn et al, "Improved speech quality and efficient vector quantization in CELP" (Proc. ICASSP, pp. 155-158, 1988: hereinafter referred to as Document 2), and so on.

In the conventional method, on a transmission side, spectral parameters representative of spectral characteristics of a speech signal are extracted from the speech signal for each frame (e.g. 20ms long) by the use of a linear predictive (LPC) analysis. Then, each frame is divided into subframes (e.g. 5ms long). For each subframe, parameters (a gain parameter and a delay parameter corresponding to a pitch period) are extracted from an adaptive codebook on the basis of a preceding excitation signal. By the use of an adaptive codebook, the speech signal of the subframe is pitch-predicted. For an excitation signal obtained by the pitch prediction, an

The excitation code vector is selected so as to minimize error power between a signal synthesized by the selected noise signal and the above-mentioned residual signal.

However, there are two major problems in the above-mentioned conventional method.

A first one of the problems is that a large amount of calculation is required to select the optimum excitation code vector from the excitation codebook.

This is because, in the methods described in Document 1 and Document 2, filtering or a convolution operation should be carried out for each code vector in order to select the excitation code vector. Besides, the operation is repeated multiple times equal in number to code vectors stored in the codebook..

For example, in case where the codebook has B bits and N dimensions, let the filter length or the impulse response length upon the filtering or the convolution operation be represented by K. Then, the amount of calculation of $N \times K \times 2^B \times 8000/N$ is required per second.

By way of example, consideration will be made about the case where $B = 10$, $N = 40$, and $k = 10$. In this case, the number

In order to reduce an amount of calculations required to search the excitation codebook, various methods have been proposed.

According to the method described in Document 3, an excitation signal is expressed by a plurality of pulses, and furthermore, each of positions of the pulses is represented by a predetermined number of bits and is transmitted. Herein, the amplitude of each pulse is restricted to +1.0 or -1.0. Therefore, the amount of calculations required to search the pulses can considerably be reduced.

Summary of the Invention:

In the light of the above-mentioned problems arising in the conventional methods, it is an object of this invention to provide a speech coder, a speech decoder, a speech coding method

In order to achieve the above-mentioned object, a speech coder according to a first aspect of the present invention comprises spectral parameter calculating means supplied with a speech signal for calculating spectral parameters, and quantizing the speech signal; impulse response calculating means for converting said spectral parameters into impulse responses; adaptive codebook means for calculating a delay and a gain from a preceding quantized excitation signal by the use of an adaptive codebook, predicting the speech signal to calculate a residue signal, and outputting said delay and said gain; and excitation quantization means for representing excitation signal of said speech signal by a combination of a plurality of pulses having nonzero amplitudes, and quantizing said excitation signal and said gain by the use of said impulse responses. The excitation quantization means holds a plurality of sets for positions of said pulses, calculates distortion between said speech signal and each of said plurality of sets by the use of said impulse responses, selects a set for positions minimizing said distortion, and outputs judgement codes representative of the selected set, so that the pulse position is quantized.

According to a second aspect of the present invention, it is desirable that the speech coder further comprises multiplexer means for producing a combination of the output of said spectral parameter calculating means, the output of said adaptive codebook means, and the output of said excitation

quantization means.

A speech coder according to a third aspect of the present invention comprises spectral parameter calculating means supplied with a speech signal for calculating, quantizing spectral parameters; impulse response calculating means for converting said spectral parameters into impulse responses; adaptive codebook means for calculating a delay and a gain from a preceding quantized excitation signal by the use of an adaptive codebook, predicting the speech signal to calculate a residue signal, and outputting said delay and said gain; and excitation quantization means for representing excitation signal of said speech signal by a combination of a plurality of pulses having nonzero amplitudes, and quantizing and outputting said excitation signal and said gain by the use of said impulse responses. The excitation quantization means holds a plurality of sets for positions of said pulses, calculates distortion between said speech signal and each of said plurality of sets by the use of said impulse responses, selects at least one set for positions minimizing said distortion, reads gain code vectors out of a gain codebook for each of said plurality of sets to quantize a gain, calculates distortion between said speech signal and the gain, selects a combination of said position minimizing said distortion and said gain code vectors, and outputs judgement codes representative of the selected set for positions.

According to a fourth aspect of the present invention, it is desirable that the speech coder further comprises multiplexer means for producing a combination of the output of said spectral parameter calculating means, the output of said

A speech coder according to a fifth aspect of the present invention comprises spectral parameter calculating means supplied with a speech signal for calculating and quantizing spectral parameters; impulse response calculating means for converting said spectral parameters into impulse responses; adaptive codebook means for calculating a delay and a gain from a preceding quantized excitation signal by the use of an adaptive codebook, predicting the speech signal to calculate a residue signal, and outputting said delay and said gain; and excitation quantization means for representing excitation signal of said speech signal by a combination of a plurality of pulses having nonzero amplitudes, and quantizing and outputting said excitation signal and said gain by the use of said impulse responses. The excitation quantization means comprises mode judging means for judging and outputting a mode by extracting feature quantities from the speech signal; and in the case where the output of said judging means is a predetermined mode. The excitation quantization means holds a plurality of sets for positions of said pulses, calculates distortion between said speech signal and each of said plurality of sets by the use of said impulse responses, selects a set for positions minimizing said distortion, and outputs judgement codes representative of the selected set for positions, so that the pulse position is quantized.

According to a sixth aspect of the present invention, it is desirable that the speech coder further comprises multiplexer means for producing a combination of the output of

A speech coder according to a seventh aspect of the present invention comprises plural position-sets storing means for holding a plurality of sets for positions of pulses; and excitation quantization means for calculating distortion between a speech signal and each of said plurality of sets, so as to select a set for positions minimizing said distortion.

A speech decoder according to a ninth aspect of the present invention comprises demultiplexer means supplied with a first code for spectral parameters, a second code for an adaptive codebook, a third code for an excitation signal, a fourth code representative of a selected set for positions, a fifth code representative of a gain, and a sixth code

A speech coding method according to a tenth aspect of the present invention comprising first step of responding to a speech signal to calculate spectral parameters and to quantize the speech signal; second step of converting said spectral parameters into impulse responses; third step of calculating a delay and a gain from a previous quantized excitation signal by the use of an adaptive codebook, predicting the speech signal to calculate a residue signal; and fourth step of representing excitation signal of said speech signal by a combination of a plurality of pulses having nonzero amplitudes, quantizing said excitation signal and said gain by the use of said impulse responses, calculating distortion between said speech signal and each of said plurality of sets for positions of pulses by the use of said impulse responses, selecting a set for positions minimizing said distortion, and outputs judgement codes representative of the selected set, so that the pulse position is quantized.

According to an eleventh aspect of the present invention, it is desirable that the speech coding method further comprises

A speech coding method according to a twelfth aspect of the present invention comprises a first step of responding to a speech signal to calculate and quantize spectral parameters; second step of converting said spectral parameters into impulse responses; third step of calculating a delay and a gain from a preceding quantized excitation signal by the use of an adaptive codebook, and predicting the speech signal to calculate a residue signal; and fourth step of representing excitation signal of said speech signal by a combination of a plurality of pulses having nonzero amplitudes, quantizing said excitation signal and said gain by the use of said impulse responses, calculating distortion between said speech signal and each of said plurality of sets for positions of said pulses by the use of said impulse responses, selecting at least one set for positions minimizing said distortion, reads gain code vectors out of a gain codebook for each of said plurality of sets to quantize a gain, calculating distortion between said speech signal and the gain, selecting a combination of said position minimizing said distortion and said gain code vectors, and outputting judgement codes representative of the selected set for positions.

According to a thirteenth aspect of the present invention, it is desirable that the speech coding method further comprises a step of producing a combination of the outputs of said first, said second and said fourth steps.

A speech coding method according to a fourteenth aspect of the present invention comprises first step of responding to

According to a fifteenth aspect of the present invention, it is desirable that the speech coding method further comprises a step of producing a combination of the outputs of said first, said second, said fourth and said fifth steps.

A speech decoding method according to a seventeenth aspect of the present invention comprises: first step of responding

According to an eighteenth aspect of the present invention, a speech decoding method comprises; first step of responding to a first code for spectral parameters, a second code for an adaptive codebook, a third code for an excitation signal, a fourth code representative of a selected set for positions, a fifth code representative of a gain, and a sixth code representative of a mode, demultiplexing them into each code; second step of producing adaptive code vectors by the use of said second code, and furthermore, in the case where said sixth code is a predetermined mode, producing pulses having nonzero amplitudes for the selected set for positions by the use of said third and said fourth codes, and producing an excitation signal by multiplying them by the gain based on said fifth code; and third step of, in response to said excitation signal, producing a reproduced signal.

Fig. 1 is a block diagram showing the speech coder according to a first embodiment of this invention.

The spectral parameter calculating circuit 200 opens a window (e.g. 24 ms long) longer than the subframe length in response to at least one subframe of the speech signal and extracts a speech, thereby calculating spectral parameters with a predetermined degree (e.g. $P = 10$).

In addition, the spectral parameter calculating circuit 200 converts linear prediction coefficients α_1 ($1 = 1, \dots, 10$) calculated by the Burg analysis into LSP parameters suitable for quantization and interpolation on the basis of the LSP codebook 211. For the conversion from the linear prediction coefficients into the LSP parameters, reference may be made to Sugamura et al, "Speech Data Compression by Linear Spectral Pair (LSP) Speech Analysis-Synthesis Technique" (Journal of the Electronic Communications Society of Japan, J64-A, pp. 599-606, 1981: hereinafter referred to as Document 5).

For example, the linear prediction coefficients calculated by the Burg analysis for a second subframe are

The linear prediction coefficients α_{11} ($i = 1, \dots, 10$, $l = 1, 2$) of the first and the second subframes, calculated as mentioned above, are delivered from the spectral parameter calculating circuit 200 to the perceptual weighting circuit 230.

The spectral parameter quantization circuit 210 efficiently quantizes a LSP parameter of a predetermined subframe to produce a quantization value which minimizes the distortion D, in accordance with the following equation (1).

In the equation (1), $LSP(i)$, $QLSP(i)$, $W(i)$ represent an i -th order LSP coefficient before quantization, a j -th result after quantization, and a weighting factor, respectively.

For the vector quantization of the LSP parameters, well-known techniques can be applied. For the details of the techniques, reference can be made to the description in Japan

Patent Laid-Open No. H04-171500 (hereinafter referred to as Document 6), Japan Patent Laid-Open No. H04-363000 (hereinafter referred to as Document 7), Japan Patent Laid-Open No. H05-6199 (hereinafter referred to as Document 8), T. Nomura et al, "LSP Coding Using VQ-SVQ With Interpolation in 4.075 kbps M-LCELP Speech Coder" (Proc. Mobile Multimedia Communications, pp. B.2.5, 1993: hereinafter referred to as Document 9), and so forth. Hence, explanation of the details of the techniques is omitted herein.

On the basis of the LSP parameters quantized for the second subframe, the spectral parameter quantization circuit 210 restores or reproduces the LSP parameters of the first and the second subframes. More specifically, the spectral parameter quantization circuit 210 carries out the linear interpolation between the quantized LSP parameters of the second subframe of a current frame and the quantized LSP parameters of the second subframe of a previous frame immediately before the current frame. As the result of the linear interpolation, the LSP parameters of the first and the second subframes can be reproduced. Then, the spectral parameter quantization circuit 210 selects one kind of the code vectors which minimizes the error power between the LSP parameters before quantization and the LSP parameters after quantization. Thereafter, the spectral parameter quantization circuit 210 reproduces the LSP parameters of the first and the second subframes by carrying out the linear interpolation.

In order to further improve the performance, the spectral parameter quantization circuit 210 may select a plurality of

0552274-054004

The spectral parameter quantization circuit 210 converts the LSP parameters of the first and the second subframes reproduced in the manner mentioned above and the quantized LSP parameters of the second subframe into the linear prediction coefficients α_{*1l} ($l = 1, \dots, 10, l = 1, 2$) for each subframe, and outputs the linear prediction coefficients α_{*1l} into the impulse response calculating circuit 310.

Supplied from the spectral parameter calculating circuit 200 with the linear prediction coefficients α_{11} ($1 = 1, \dots, 10, 1 = 1, 2$) before quantization for each subframe, the perceptual weighting circuit 230 carries out the perceptual weighting, in a manner mentioned in Document 1, for the speech signal of the subframe and produces a perceptual weighted signal.

As shown in Fig. 1, the response signal calculating circuit 240 is supplied from the spectral parameter calculating circuit 200 with the linear prediction coefficients α_{11} for each subframe and is also supplied from the spectral parameter

$$x_z(n) = d(n) - \sum_{i=1}^{10} \alpha_i d(n-i) + \sum_{i=1}^{10} \alpha_i \gamma^i y(n-i) + \sum_{i=1}^{10} \alpha'_i \gamma^i x_x(n-i) \quad \dots \quad (2)$$
$$y(n-i) = p(N + (n-i)) \quad \dots \quad (3)$$
$$x_r(n-i) = s_r(N + (n-i)) \dots (4)$$

The subtracter 235 subtracts the response signal for one subframe from the perceptual weighted signal delivered from the perceptual weighting circuit 230, calculates $x'_w(n)$ in accordance with the following equation (5), and delivers the calculated $x'_w(n)$ to the adaptive codebook circuit 500.

$$x'_w(n) = x_w(n) - x_r(n) \quad \dots (5)$$

The impulse response calculating circuit 310 calculates a predetermined number L of impulse responses $H_i(n)$ of a perceptual weighting filter whose z transform is expressed by the following equation (6), and delivers the calculated impulse responses $H_i(n)$ to the adaptive codebook circuit 500, the excitation quantization circuit 350 and the gain quantization circuit 370.

$$H_w(z) = \frac{1 - \sum_{i=1}^{10} \alpha_i z^{-i}}{1 - \sum_{i=1}^{10} \alpha_i \gamma^i z^{-i}} \frac{1}{1 - \sum_{i=1}^{10} \alpha_i \gamma^i z^{-i}} \quad \dots (6)$$

The adaptive codebook circuit 500 is supplied with a preceding excitation signal $v(n)$ from the gain quantization circuit 365, the output signal $x'_w(n)$ from the subtractor 235, and the perceptual weighted impulse response $H_i(n)$ from the impulse response calculating circuit 310. The adaptive codebook circuit 500 calculates a delay T corresponding to a pitch such that distortions in the following equations (7) and (8) are minimized, and delivers an index representative of the delay T to the multiplexer 400.

$$D_T = \sum_{n=0}^{N-1} x_w'^2(n) - \left[\sum_{n=0}^{N-1} x'_w(n) y_w(n-T) \right]^2 / \left[\sum_{n=0}^{N-1} y_w^2(n-T) \right] \quad \dots (7)$$

$$y_w(n-T) = v(n-T) * h_w(n) \quad \dots (8)$$

In the equation (8), the symbol $*$ represents a convolution operation.

A gain β is calculated in accordance with the following equation (9).

09852274:054004

$$\beta = \sum_{n=0}^{N-1} x'_w(n) y_w(n-T) / \sum_{n=0}^{N-1} y_w^2(n-T) \quad \dots (9)$$

Herein, in order to improve the accuracy in extracting the delay with respect to a female sound or a child voice, the delay may be obtained from a sample value having floating point, instead of a sample value consisting of integral numbers. The details of the technique are disclosed, for example, in P. Kroon et al, "Pitch predictors with high temporal resolution" (Proc. ICASSP, pp. 661-664, 1990: hereinafter referred to as Document 11) and so on.

Furthermore, the adaptive codebook circuit 500 carries out pitch prediction in accordance with the following equation (10) and delivers a prediction residual signal $e_w(n)$ to the excitation quantization circuit 350.

$$e_w(n) = x'_w(n) - \beta v(n-T) * h_w(n) \quad \dots (10)$$

The excitation quantization circuit 350 produces the excitation signal for subframes represented by M pulses.

In the illustrated example, the plural position-sets storing circuit 450 stores a plurality of sets of positions in advance. For example, it is assumed that M is equal to four in the following. In this event, four sets of positions are stored, which are shown in the Tables 1 through 4, respectively. Herein, it is noted that a first pulse in Tables 1 through 4 is generated at either one of four candidate positions 0, 20, 40, and 60 while the remaining pulses are generated at candidate positions shown in Tables 1 through 4.

Pulse Number	set of positions
first pulse	0, 20, 40, 60
second pulse	1, 21, 41, 61
	2, 22, 42, 62
	3, 23, 43, 63
	4, 24, 44, 64

	16, 36, 56, 76
third pulse	17, 37, 57, 77
	18, 38, 58, 78
fourth pulse	19, 39, 59, 79

Pulse Number	set of positions
first pulse	0, 20, 40, 60
	1, 21, 41, 61

	15, 35, 55, 75
second pulse	16, 36, 56, 76
	17, 37, 57, 77
third pulse	18, 38, 58, 78
fourth pulse	19, 39, 59, 79

In order to collectively quantize pulse amplitudes for the M pulses, the speech coder 10 further comprises a polarity codebook or an amplitude codebook of B bits. In the following, description will be made about the case where the polarity codebook is used. The polarity codebook is stored in the

The excitation quantization circuit 350 reads polarity code vectors out of the excitation codebook 351, assigns each code vector with each position of the foregoing first through fourth sets of positions, and selects a combination of the code vector and the set of positions such that the combination minimizes the following equation (11).

In the equation (11), $h_v(n)$ is a perceptual weighted impulse response.

$$D(k,i) = [\sum_{n=0}^{N-1} e_w(n) s_{wk}(m_i)]^2 / \sum_{n=0}^{N-1} s_{wk}^2(m_i) \quad \dots \quad (12)$$
$$D(k, j) = \left[\sum_{n=0}^{N-1} \phi(n) v_k(n) \right]^2 / \sum_{n=0}^{N-1} s_{wk}^2(m_i) \dots (13)$$

After searching the polarity code vector $g_{i,k}$, the excitation quantization circuit 350 supplies the gain quantization circuit 370 with the selected combination of the polarity code vector $g_{i,k}$ and the set of positions .

Supplied with the combination of the polarity code vector g_{ik} and the position set from the excitation quantization circuit 350, the gain quantization circuit 370 reads gain code vectors out of the gain codebook 380 and selects the gain code vector such that the following equation (15) is minimized.

$$D_k = \sum_{n=0}^{N-1} [x_w(n) - \beta'_i v(n-T) * h_w(n) - G'_i \sum_{i=1}^M g'_{ik} h_w(n-m_i)]^2 \quad \dots \quad (15)$$

The above description was made about the case where the gain quantization circuit 365 carries out vector quantization simultaneously upon both of a gain of the adaptive codebook and a gain of an excitation expressed by pulses. The gain quantization circuit 370 delivers, to the multiplexer 400, the index indicative of the selected polarity code vector, the codes representative of the position, and the index indicative of the gain code vector.

The codebook may be preliminarily obtained and stored by learning from the speech signal. The learning method of the codebook is disclosed, for example, in Linde et al, "An algorithm for vector quantization design" (IEEE Trans. Commun., pp. 84-95, January, 1980: hereinafter referred to as Document 12).

The weighted signal calculating circuit 360 is supplied with the indexes and reads the code vector corresponding to each index. Then, the weighted signal calculating circuit 360 calculates a drive excitation signal $v(n)$ in accordance with the following equation (16).

$$v(n) = \beta'_{\mathbf{i}} v(n-T) + G' \sum_{i=1}^M g'_{\mathbf{i}k} \delta(n-m_i) \quad \dots \quad (16)$$

The drive excitation signal $v(n)$ is delivered from the weighted signal calculating circuit 360 to the multiplexer 400 and the adaptive codebook circuit 500.

Next, by the use of the output parameter of the spectral parameter calculating circuit 200 and the output parameter of the spectral parameter quantization circuit 210, the weighted signal calculating circuit 360 calculates the response signal $s_r(n)$ for each subframe in accordance with the following equation (17), and delivers the response signal $s_r(n)$ to the response signal calculating circuit 240.

$$s_W(n) = v(n) - \sum_{i=1}^{10} \alpha_i v(n-i) + \sum_{i=1}^{10} \alpha_i \gamma^i p(n-i) + \sum_{i=1}^{10} \alpha'_i \gamma^i s_W(n-i) \quad \dots \quad (17)$$

Fig. 2 is a block diagram of a speech coder 20 according to a second embodiment of this invention. The common numerical references are labeled in the speech coder 20 of the second embodiment shown in Fig. 2 to the components which correspond to those in the speech coder 10 of the first embodiment shown in Fig. 1. In this connection, it is readily understood that the respective components in the speech coders 10 and 20 are operable in the same manner.

With respect to the following points, operations of the speech coder 20 according to the second embodiment shown in Fig. 2 differ from those of the speech coder 10 according to the first embodiment shown in Fig. 1.

As an example, in the case where the number of types of modes is set to 2, the types of modes are mode 0 and mode 1, which correspond to a utterance period and a silence period, respectively.

The excitation quantization circuit 358 is supplied with the mode judgement information from the mode judging circuit 800. If the mode represented by the mode judgement information is mode 1, the excitation quantization circuit 358 refers to the polarity codebook for the plural sets of positions, selects a set of positions and a code vector which make the equation (11) be minimized, and outputs the selected set of positions and the selected code vector. If the mode represented by the mode judgement information is mode 0, the excitation quantization circuit 358 refers to the polarity codebook for a pulse set, which is preliminarily selected to be for example any one of sets shown in the Tables 1 through 4, and selects and outputs a set of positions and a code vector which make the

equation (11) be minimized.

Supplied with the mode judgement information from the mode judging circuit 800, the gain quantization circuit 378 reads gain code vectors out of the gain codebook 380, searches, with respect to the selected combination of the polarity code vector and the position, the gain code vector which makes the equation (15) be minimized, and selects a combination of the gain code vector, the polarity code vector and the position, the newly selected combination making the distortion be minimized.

Fig. 4 is a block diagram of a speech decoder 40 according to a fourth embodiment of this invention. The speech decoder 40 according to this embodiment comprises a demultiplexer 505, a gain codebook 380, a decoding circuit 510, an adaptive codebook circuit 520, an excitation signal restoration reproduction circuit 540, an excitation codebook 351, an adder 550, a synthesis filter circuit 560, a spectral parameter decoding circuit 570, a plural position-sets storing circuit 580.

The speech decoder 40 according to the fourth embodiment is operable in the following manner. The demultiplexer 505 demultiplexes a code sequence into a position-set judgement information, an index indicative of a gain code vector, an index indicative of a delay on the adaptive codebook, information of the excitation signal, an index indicative of the excitation code vector, an index indicative of a spectral parameter.

The gain decoding circuit 510 is supplied from the demultiplexer with the index indicative of the gain code vector, reads a gain code vector out of the gain codebook 380 in

The adaptive codebook circuit 520 is supplied from the demultiplexer 505 with the delay of the adaptive codebook, produces an adaptive code vector, multiplies the adaptive code vector by the gain of the adaptive codebook based on the gain code vector, and outputs the adaptive code vector.

Furthermore, the excitation signal restoration circuit 540 produces an excitation pulse by the use of the polarity code vector and the gain code vector both read out of the excitation codebook 351, and delivers the excitation pulse to the adder 550.

The spectral parameter decoding circuit 570 decodes the spectral parameters, converts the spectral parameters into linear prediction coefficients, and delivers the linear prediction coefficients to the synthesis filter circuit 560.

The synthesis filter circuit 560 is supplied with the drive excitation signal $v(n)$ and the linear prediction coefficients from the adder 550 and the spectral parameter

An excitation signal restoration circuit 590 of the speech decoder 50 according to this embodiment is supplied with the mode judgement information and the position-set judgment information. If the mode represented by the mode judgement information is mode 1, the excitation signal restoration circuit 590 reads, out of the plural position-sets storing circuit 580, a set of positions which is selected on the basis of the position-set judgement information. Also, the excitation signal restoration circuit 590 produces an excitation pulse by the use of the polarity code vector and the gain code vector both read out of the excitation codebook 351, and delivers the excitation pulse to the adder 550. On the other hand, if the mode represented by the mode judgement information is mode 0, the excitation signal restoration circuit 590 produces an excitation pulse by the use of the predetermined pulse of the set of positions and the gain code vector, and

Although the above-mentioned first through fifth embodiments provide the examples of the speech coders and the speech decoders, those skilled in the art can readily understand every steps of speech coding methods and speech decoding methods according to the present invention, on the basis of the descriptions for the apparatuses.

According to this invention, a speech coding system selects at least one set of positions which minimize the distortion between a speech signal and them. For each position set, the speech coding system searches gain code vectors stored in a gain codebook so as to calculate a distortion between them and a speech signal as the primary reproduced signal. Then, the speech coding system selects a combination of the set of positions and the gain code vector so as to minimize the distortion between the combination and a speech signal. Hence, the present invention can provides the speech coding system where the distortion is minimized on the primary reproduced

speech signal including a gain code vector and the sound quality is improved.

According to the speech coding system of this invention, a speech decoding system receives judgement codes, and selects, from a plurality of sets of positions, a set of positions which is selected on transmission side. Then the speech decoding system generates pulses with the selected set of positions, multiplies the generated pulses by a gain, and filters them at the synthesis filter circuit so as to reproduce a speech signal. Therefore, the present invention can provides the speech decoding system where the sound quality is improved in comparison with the conventional system, even if the bit rate is low.

00000000-051001